



## NOKIA® CPRI Digital Donor CPRI-N V7.0 supported

- Supports up to 24 AxCs per card in FDD mode
- Supports up to 4 AxCs per card in TDD mode
- Supports Line Rates 3, 5 and 7 and auto-negotiation of the line rate in FDD mode
- Supports Line Rate 7 in TDD mode

## Product Classification

<b>Product Type</b>	Card
<b>Product Brand</b>	ERA®

## General Specifications

<b>Device Type</b>	Card
<b>General Alarm</b>	Integrated into management system
<b>Input Connector Interface</b>	SFP+
<b>Input Connector, quantity</b>	6
<b>Management Interface</b>	Integrated into management system
<b>Note</b>	Detailed Product Specifications are available. Please contact your local CommScope representative.
<b>Required Subrack Version</b>	WCS-2 SUBRACK (7635443-03)   WCS-2 SUBRACK (A7635443-03)   WCS-4 SUBRACK (7635442-03)   WCS-4 SUBRACK (A7635442-03)   WCS2 SUBRACK, INTEGRATED DC PSU (7844067-02)   WCS2 SUBRACK, INTEGRATED DC PSU (A7844067-02)   WCS4 SUBRACK, INTEGRATED DC PSU (7844068-02)   WCS4 SUBRACK, INTEGRATED DC PSU (A7844068-02)

## Dimensions

<b>Height</b>	20 mm   0.787 in
<b>Width</b>	145 mm   5.709 in
<b>Depth</b>	300 mm   11.811 in

## Packaging and Weights

<b>Weight, net</b>	0.47 kg   1.036 lb
--------------------	--------------------