

14-port, 1.8m, multiband antenna, RF port assignments are as follows: R1 = 694-862, R2 = 880-960, G1 = 1427-1518, B1 & B2 = 1695-2180 and Y1 & Y2 = 2490-2690 MHz, 65° HPBW, 6x RET with manual override. Y1 & Y2 share a common RET

- Electrical tilt settings applicable to RF Ports R1, R2, G1, B1 & B2 can be set independently (See Array Layout and RET Table below)
- A common electrical tilt setting is shared by RF Ports Y1 & Y2
- All Internal RET actuators are connected in "Cascaded SRET" configuration
- Retractable tilt indicator rods

OBSOLETE

This product was discontinued on: March 31, 2021

General Specifications

Antenna Type	Sector
Band	Multiband
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage
Radome Material	Fiberglass, UV resistant
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, high band	10
RF Connector Quantity, low band	4
RF Connector Quantity, total	14

Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	8-pin DIN Female 8-pin DIN Male
RET Interface, quantity	1 female 1 male
Input Voltage	10-30 Vdc

Page 1 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



Power Consumption, idle state, maximum	1 W
Power Consumption, normal conditions, maximum	8 W
Protocol	3GPP/AISG 2.0 (Single RET)
Dimensions	
Width	350 mm 13.78 in
Depth	208 mm 8.189 in
Length	1828 mm 71.969 in
Net Weight, without mounting kit	33 kg 72.752 lb

Array Layout


	Array	Freq (MHz)	Conns	RET (SRET)	AISG RET UID
R2	R1	694-862	1-2	1	CPxxxxxxxxxxxxR1
	R2	880-960	3-4	2	CPxxxxxxxxxxxxR2
	G1	1427-1518	5-6	3	CPxxxxxxxxxxxxxG1
В2	B1	1695-2180	7-8	4	CPxxxxxxxxxxxXXXB1
	B2	1695-2180	9-10	5	CPxxxxxxxxxxxXB2
B1 G1	Y1	2490-2690	11-12	6	CDunning and M1
R1	Y2	2490-2690	13-14		CPxxxxxxxxxxxxXY1

Port Configuration

Page 2 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

COMMSCOPE°



Electrical Specifications

Impedance	50 ohm
Operating Frequency Band	1427 – 1518 MHz 1695 – 2180 MHz 2490 – 2690 MHz 694 – 862 MHz 880 – 960 MHz
Polarization	±45°
Total Input Power, maximum	800 W @ 50 °C

Electrical Specifications

	R1	R2	G1	B1	B2	Y1	Y2
Frequency Band, MHz	694-862	880-960	1427-1518	1695-2180	1695-2180	2490-2690	2490-2690
Gain, dBi	15	15.2	16.2	17.8	17.4	17.9	17.4
Beamwidth, Horizontal, degrees	67	63	65	62	61	60	62
Beamwidth, Vertical, degrees	11.8	9.9	6.9	5.2	5.2	4.2	4.1
Beam Tilt, degrees	2-14	2-14	2-12	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	15	17	17	17	15	19	19
Front-to-Back Ratio at 180°, dB	31	33	32	31	35	33	34
Isolation, Cross Polarization, dB	28	28	28	28	28	28	28

Page 3 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

COMMSCOPE°

Isolation, Inter-band, dB	30	30	30	30	30	30	30
VSWR Return loss, dB	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0
PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150	-150
Input Power per Port, maximum, watts	350	350	300	300	300	250	250

Electrical Specifications, BASTA

Frequency Band, MHz	694-862	880-960	1427-1518	1695-2180	1695-2180	2490-2690	2490-2690
Gain by all Beam Tilts, average, dBi	14.7	15	16	17.5	16.9	17.7	17.1
Gain by all Beam Tilts Tolerance, dB	±0.4	±0.4	±0.4	±0.7	±0.7	±0.4	±0.5
Gain by Beam Tilt, average, dBi	2 ° 14.8 8 ° 14.7 14 ° 14.6	2 ° 15.1 8 ° 15.1 14 ° 14.9	2 ° 15.8 7 ° 16.1 12 ° 16.0	2 ° 17.3 7 ° 17.6 12 ° 17.4	2 ° 16.8 7 ° 17.0 12 ° 16.8	2 ° 17.6 7 ° 17.8 12 ° 17.2	2 ° 17.2 7 ° 17.3 12 ° 16.7
Beamwidth, Horizontal Tolerance, degrees	±1.9	±2.3	±6.3	±3.2	±3.2	±3.8	±5.6
Beamwidth, Vertical Tolerance, degrees	±1.2	±0.4	±0.3	±0.5	±0.6	±0.2	±0.2
USLS, beampeak to 20° above beampeak, dB	15	17	17	16	14	16	16
Front-to-Back Total Power at 180° ± 30°, dB	25	23	25	26	29	27	28
CPR at Boresight, dB	20	23	15	20	23	18	20
CPR at Sector, dB	11	10	7	9	8	9	5

Mechanical Specifications

Wind Loading @ Velocity, frontal	301.0 N @ 150 km/h (67.7 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	254.0 N @ 150 km/h (57.1 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	638.0 N @ 150 km/h (143.4 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	319.0 N @ 150 km/h (71.7 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

Packaging and Weights

Width, packed	456 mm 17.953 in
Depth, packed	357 mm 14.055 in
Length, packed	1975 mm 77.756 in
Weight, gross	46.5 kg 102.515 lb

Page 4 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

COMMSCOPE°

Regulatory Compliance/Certifications

Agency

Classification

CE

ISO 9001:2015



Included Products

BSAMNT-3	 Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.
SMALL-CAPKIT	– Female End Cap Assembly for 4.3-10 series and 4.1-9.5 Din, work torque 5-8N/M.
* Footnotes	

Designed, manufactured and/or distributed under this quality management system

Performance Note Severe environmental conditions may degrade optimum performance

Compliant with the relevant CE product directives

Page 5 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

