

18-port sector antenna, 6x 694-960, 12x 1695-2690 MHz, 65° HPBW, 9xRET

- All Internal RET actuators are connected in "Cascaded SRET" configuration
- Supports re-configurable antenna sharing capability enabling control of the internal RET system using up to two separate RET compatible OEM radios

#### General Specifications

**Antenna Type** Sector

**Band** Multiband

Color Light Gray (RAL 7035)

**Grounding Type** RF connector inner conductor and body grounded to reflector and mounting

bracket

12

**Performance Note** Outdoor usage

**Radome Material** Fiberglass, UV resistant

**Reflector Material** Aluminum

**RF Connector Interface** 4.3-10 Female

**RF Connector Location** Bottom

RF Connector Quantity, mid band RF Connector Quantity, low band

RF Connector Quantity, total 18

### Remote Electrical Tilt (RET) Information

**RET Hardware** CommRET v2

**RET Interface** 8-pin DIN Female | 8-pin DIN Male

2 female | 2 male **RET Interface, quantity** 

**Input Voltage** 10-30 Vdc

**Internal RET** Low band (3) | Mid band (6)

Power Consumption, active state, maximum 8 W Power Consumption, idle state, maximum 1 W

Protocol 3GPP/AISG 2.0

**Dimensions** 

**COMMSCOPE®** 


**Width** 579 mm | 22.795 in

**Depth** 212 mm | 8.346 in

**Length** 2100 mm | 82.677 in

Net Weight, antenna only 47.7 kg | 105.16 lb

## Array Layout



Array ID	Frequency (MHz)	RF Connector	RET (SRET)	AISG No.	AISG RET UID
R1	694-960	1 - 2	1	AISG1	CPxxxxxxxxxxxxxxR1
R2	694-960	3 - 4	2	AISG1	CPxxxxxxxxxxxxxxR2
R3	694-960	5 - 6	3	AISG1	CPxxxxxxxxxxxxxR3
Y1	1695-2690	7 - 8	4	AISG1	CPxxxxxxxxxxxxxY1
Y2	1695-2690	9 - 10	5	AISG1	CPxxxxxxxxxxxxxY2
Y3	1695-2690	11 - 12	6	AISG1	CPxxxxxxxxxxxxxY3
Y4	1695-2690	13 - 14	7	AISG1	CPxxxxxxxxxxxx4
Y5	1695-2690	15 - 16	8	AISG1	CPxxxxxxxxxxxxxY5
Y6	1695-2690	17 - 18	9	AISG1	CPxxxxxxxxxxxxxY6

(Sizes of colored hoxes are not true denictions of array sizes)

## Port Configuration



### **Electrical Specifications**

**Impedance** 50 ohm

**Operating Frequency Band** 1695 – 2690 MHz | 694 – 960 MHz

Polarization ±45°

**Total Input Power, maximum** 900 W @ 50 °C

## Electrical Specifications, BASTA

Frequency Band, MHz	698-806	790-894	890-960	698-806	790-894	890-960
Gain by all Beam Tilts, average, dBi	13.8	14.3	14.8	12.3	13.6	14.7
USLS, beampeak to 20° above beampeak, dB	14	15	13	12	16	16

Page 3 of 6



CPR at Boresight, dB	18	18	21	16	18	22
CPR at Sector, dB	10	6	6	8	6	6

#### **Electrical Specifications**

Frequency Band, MHz 1695-1900

Isolation, Cross Polarization,

port to port, dB

#### Electrical Specifications, BASTA

Frequency Band, MHz	1695-1990	1920-2300	2300-2500	2490-2690
Gain by all Beam Tilts, average, dBi	16.1	16.9	17.8	17.9
USLS, beampeak to 20° above beampeak, dB	15	15	16	16
CPR at Boresight, dB	18	18	19	21
CPR at Sector, dB	6	3	5	5

987

#### Electrical Specifications, BASTA

Frequency Band, MHz	1695-1990	1920-2300	2300-2500	2490-2690
Gain by all Beam Tilts, average, dBi	15.9	16.7	17.3	17.3
USLS, beampeak to 20° above beampeak, dB	11	12	12	13
CPR at Boresight, dB	19	21	21	22
CPR at Sector, dB	5	3	4	2

#### Mechanical Specifications

 Wind Loading @ Velocity, frontal
 576.0 N @ 150 km/h (129.5 lbf @ 150 km/h)

 Wind Loading @ Velocity, lateral
 241.0 N @ 150 km/h (54.2 lbf @ 150 km/h)

 Wind Loading @ Velocity, maximum
 919.0 N @ 150 km/h (206.6 lbf @ 150 km/h)

 Wind Loading @ Velocity, rear
 584.0 N @ 150 km/h (131.3 lbf @ 150 km/h)

Wind Speed, maximum 241 km/h (150 mph)

#### Packaging and Weights

 Width, packed
 681 mm | 26.811 in

 Depth, packed
 368 mm | 14.488 in

 Length, packed
 2239 mm | 88.15 in

**COMMSCOPE®** 

**Weight, gross** 62.3 kg | 137.348 lb

#### Regulatory Compliance/Certifications

Agency Classification

CHINA-ROHS Below maximum concentration value

ISO 9001:2015 Designed, manufactured and/or distributed under this quality management system

REACH-SVHC Compliant as per SVHC revision on www.commscope.com/ProductCompliance

ROHS Compliant UK-ROHS Compliant



#### Included Products

BSAMNT-4 — Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

#### \* Footnotes

**Performance Note** Severe environmental conditions may degrade optimum performance



# BSAMNT-4



Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

#### **Product Classification**

**Product Type** Downtilt mounting kit

General Specifications

ApplicationOutdoorColorSilver

**Dimensions** 

Compatible Diameter, maximum115 mm | 4.528 inCompatible Diameter, minimum60 mm | 2.362 inWeight, net6.5 kg | 14.33 lb

Material Specifications

Material Type Galvanized steel

### Packaging and Weights

Included Brackets | Hardware

Packaging quantity 1

#### Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.commscope.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant

